- **TABLE 3.1**: PROPERTIES OF CONTINUOUS-TIME FOURIER SERIES

Property	Section	Periodic Signal	Fourier Series Coefficients
		$\left.\begin{array}{l} x(t) \\ y(t) \end{array}\right\}$ Periodic with period T and fundamental frequency $\omega_0 = 2\pi/T$	a_k b_k
Linearity	3.5.1	$Ax(t) + By(t)$	$Aa_k + Bb_k$
Time Shifting	3.5.2	$x(t - t_0)$	$a_k e^{-jk\omega_0 t_0} = a_k e^{-jk(2\pi/T)t_0}$
Frequency Shifting		$e^{jM\omega_0 t}x(t) = e^{jM(2\pi/T)t}x(t)$	a_{k-M}
Conjugation	3.5.6	$x^*(t)$	a^*_{-k}
Time Reversal	3.5.3	$x(-t)$	a_{-k}
Time Scaling	3.5.4	$x(\alpha t)$, $\alpha > 0$ (periodic with period T/α)	a_k
Periodic Convolution		$\int_T x(\tau)y(t-\tau)d\tau$	$Ta_k b_k$
Multiplication	3.5.5	$x(t)y(t)$	$\sum_{l=-\infty}^{+\infty} a_l b_{k-l}$
Differentiation		$\frac{dx(t)}{dt}$	$jk\omega_0 a_k = jk\frac{2\pi}{T}a_k$
Integration		$\int_{-\infty}^{t} x(t)\,dt$ (finite valued and periodic only if $a_0 = 0$)	$\left(\frac{1}{jk\omega_0}\right)a_k = \left(\frac{1}{jk(2\pi/T)}\right)a_k$
Conjugate Symmetry for Real Signals	3.5.6	$x(t)$ real	$\begin{cases} a_k = a^*_{-k} \\ \mathcal{R}e\{a_k\} = \mathcal{R}e\{a_{-k}\} \\ \mathcal{I}m\{a_k\} = -\mathcal{I}m\{a_{-k}\} \\ \lvert a_k\rvert = \lvert a_{-k}\rvert \\ \sphericalangle a_k = -\sphericalangle a_{-k} \end{cases}$
Real and Even Signals	3.5.6	$x(t)$ real and even	a_k real and even
Real and Odd Signals	3.5.6	$x(t)$ real and odd	a_k purely imaginary and odd
Even-Odd Decomposition of Real Signals		$\begin{cases} x_e(t) = \mathcal{E}v\{x(t)\} & [x(t) \text{ real}] \\ x_o(t) = \mathcal{O}d\{x(t)\} & [x(t) \text{ real}] \end{cases}$	$\mathcal{R}e\{a_k\}$ $j\mathcal{I}m\{a_k\}$

Parseval's Relation for Periodic Signals

$$\frac{1}{T}\int_T |x(t)|^2 dt = \sum_{k=-\infty}^{+\infty} |a_k|^2$$

- **TABLE 3.2**: PROPERTIES OF DISCRETE-TIME FOURIER SERIES

Property	Periodic Signal	Fourier Series Coefficients
	$\left.\begin{array}{l} x[n] \\ y[n] \end{array}\right\}$ Periodic with period N and fundamental frequency $\omega_0 = 2\pi/N$	$\left.\begin{array}{l} a_k \\ b_k \end{array}\right\}$ Periodic with period N
Linearity	$Ax[n] + By[n]$	$Aa_k + Bb_k$
Time Shifting	$x[n - n_0]$	$a_k e^{-jk(2\pi/N)n_0}$
Frequency Shifting	$e^{jM(2\pi/N)n} x[n]$	a_{k-M}
Conjugation	$x^*[n]$	a^*_{-k}
Time Reversal	$x[-n]$	a_{-k}
Time Scaling	$x_{(m)}[n] = \begin{cases} x[n/m], & \text{if } n \text{ is a multiple of } m \\ 0, & \text{if } n \text{ is not a multiple of } m \end{cases}$ (periodic with period mN)	$\frac{1}{m} a_k \begin{pmatrix}\text{viewed as periodic} \\ \text{with period } mN\end{pmatrix}$
Periodic Convolution	$\sum_{r=\langle N\rangle} x[r]y[n-r]$	$N a_k b_k$
Multiplication	$x[n]y[n]$	$\sum_{l=\langle N\rangle} a_l b_{k-l}$
First Difference	$x[n] - x[n-1]$	$(1 - e^{-jk(2\pi/N)})a_k$
Running Sum	$\sum_{k=-\infty}^{n} x[k] \begin{pmatrix}\text{finite valued and periodic only} \\ \text{if } a_0 = 0\end{pmatrix}$	$\left(\frac{1}{(1 - e^{-jk(2\pi/N)})}\right) a_k$
Conjugate Symmetry for Real Signals	$x[n]$ real	$\begin{cases} a_k = a^*_{-k} \\ \mathcal{Re}\{a_k\} = \mathcal{Re}\{a_{-k}\} \\ \mathcal{Im}\{a_k\} = -\mathcal{Im}\{a_{-k}\} \\ \lvert a_k\rvert = \lvert a_{-k}\rvert \\ \sphericalangle a_k = -\sphericalangle a_{-k} \end{cases}$
Real and Even Signals	$x[n]$ real and even	a_k real and even
Real and Odd Signals	$x[n]$ real and odd	a_k purely imaginary and odd
Even-Odd Decomposition of Real Signals	$\begin{cases} x_e[n] = \mathcal{Ev}\{x[n]\} & [x[n] \text{ real}] \\ x_o[n] = \mathcal{Od}\{x[n]\} & [x[n] \text{ real}] \end{cases}$	$\mathcal{Re}\{a_k\}$ $j\mathcal{Im}\{a_k\}$

Parseval's Relation for Periodic Signals

$$\frac{1}{N} \sum_{n=\langle N\rangle} |x[n]|^2 = \sum_{k=\langle N\rangle} |a_k|^2$$

- **TABLE 4.1**: PROPERTIES OF THE FOURIER TRANSFORM

Section	Property	Aperiodic signal	Fourier transform
		$x(t)$	$X(j\omega)$
		$y(t)$	$Y(j\omega)$
4.3.1	Linearity	$ax(t) + by(t)$	$aX(j\omega) + bY(j\omega)$
4.3.2	Time Shifting	$x(t - t_0)$	$e^{-j\omega t_0}X(j\omega)$
4.3.6	Frequency Shifting	$e^{j\omega_0 t}x(t)$	$X(j(\omega - \omega_0))$
4.3.3	Conjugation	$x^*(t)$	$X^*(-j\omega)$
4.3.5	Time Reversal	$x(-t)$	$X(-j\omega)$
4.3.5	Time and Frequency Scaling	$x(at)$	$\frac{1}{\|a\|}X\left(\frac{j\omega}{a}\right)$
4.4	Convolution	$x(t) * y(t)$	$X(j\omega)Y(j\omega)$
4.5	Multiplication	$x(t)y(t)$	$\frac{1}{2\pi}\int_{-\infty}^{+\infty} X(j\theta)Y(j(\omega - \theta))d\theta$
4.3.4	Differentiation in Time	$\frac{d}{dt}x(t)$	$j\omega X(j\omega)$
4.3.4	Integration	$\int_{-\infty}^{t} x(t)dt$	$\frac{1}{j\omega}X(j\omega) + \pi X(0)\delta(\omega)$
4.3.6	Differentiation in Frequency	$tx(t)$	$j\frac{d}{d\omega}X(j\omega)$
4.3.3	Conjugate Symmetry for Real Signals	$x(t)$ real	$\begin{cases} X(j\omega) = X^*(-j\omega) \\ \Re e\{X(j\omega)\} = \Re e\{X(-j\omega)\} \\ \Im m\{X(j\omega)\} = -\Im m\{X(-j\omega)\} \\ \|X(j\omega)\| = \|X(-j\omega)\| \\ \sphericalangle X(j\omega) = -\sphericalangle X(-j\omega) \end{cases}$
4.3.3	Symmetry for Real and Even Signals	$x(t)$ real and even	$X(j\omega)$ real and even
4.3.3	Symmetry for Real and Odd Signals	$x(t)$ real and odd	$X(j\omega)$ purely imaginary and odd
4.3.3	Even-Odd Decomposition for Real Signals	$x_e(t) = \mathcal{E}v\{x(t)\}$ [$x(t)$ real] $x_o(t) = \mathcal{O}d\{x(t)\}$ [$x(t)$ real]	$\Re e\{X(j\omega)\}$ $j\Im m\{X(j\omega)\}$

4.3.7 Parseval's Relation for Aperiodic Signals

$$\int_{-\infty}^{+\infty} |x(t)|^2 dt = \frac{1}{2\pi}\int_{-\infty}^{+\infty} |X(j\omega)|^2 d\omega$$

TABLE 4.2: BASIC FOURIER TRANSFORM PAIRS

Signal	Fourier transform	Fourier series coefficients (if periodic)
$\sum_{k=-\infty}^{+\infty} a_k e^{jk\omega_0 t}$	$2\pi \sum_{k=-\infty}^{+\infty} a_k \delta(\omega - k\omega_0)$	a_k
$e^{j\omega_0 t}$	$2\pi\delta(\omega - \omega_0)$	$a_1 = 1$ $a_k = 0$, otherwise
$\cos \omega_0 t$	$\pi[\delta(\omega - \omega_0) + \delta(\omega + \omega_0)]$	$a_1 = a_{-1} = \frac{1}{2}$ $a_k = 0$, otherwise
$\sin \omega_0 t$	$\frac{\pi}{j}[\delta(\omega - \omega_0) - \delta(\omega + \omega_0)]$	$a_1 = -a_{-1} = \frac{1}{2j}$ $a_k = 0$, otherwise
$x(t) = 1$	$2\pi\,\delta(\omega)$	$a_0 = 1,\quad a_k = 0,\ k \neq 0$ (this is the Fourier series representation for any choice of $T > 0$)
Periodic square wave $x(t) = \begin{cases} 1, & \lvert t\rvert < T_1 \\ 0, & T_1 < \lvert t\rvert \le \frac{T}{2} \end{cases}$ and $x(t + T) = x(t)$	$\sum_{k=-\infty}^{+\infty} \frac{2\sin k\omega_0 T_1}{k}\,\delta(\omega - k\omega_0)$	$\frac{\omega_0 T_1}{\pi}\,\mathrm{sinc}\left(\frac{k\omega_0 T_1}{\pi}\right) = \frac{\sin k\omega_0 T_1}{k\pi}$
$\sum_{n=-\infty}^{+\infty} \delta(t - nT)$	$\frac{2\pi}{T}\sum_{k=-\infty}^{+\infty} \delta\left(\omega - \frac{2\pi k}{T}\right)$	$a_k = \frac{1}{T}$ for all k
$x(t)\begin{cases} 1, & \lvert t\rvert < T_1 \\ 0, & \lvert t\rvert > T_1 \end{cases}$	$\frac{2\sin \omega T_1}{\omega}$	—
$\frac{\sin Wt}{\pi t}$	$X(j\omega) = \begin{cases} 1, & \lvert\omega\rvert < W \\ 0, & \lvert\omega\rvert > W \end{cases}$	—
$\delta(t)$	1	—
$u(t)$	$\frac{1}{j\omega} + \pi\,\delta(\omega)$	—
$\delta(t - t_0)$	$e^{-j\omega t_0}$	—
$e^{-at}u(t),\ \mathcal{R}e\{a\} > 0$	$\frac{1}{a + j\omega}$	—
$te^{-at}u(t),\ \mathcal{R}e\{a\} > 0$	$\frac{1}{(a + j\omega)^2}$	—
$\frac{t^{n-1}}{(n-1)!}e^{-at}u(t)$, $\mathcal{R}e\{a\} > 0$	$\frac{1}{(a + j\omega)^n}$	—

TABLE 5.1: PROPERTIES OF THE DISCRETE-TIME FOURIER TRANSFORM

Section	Property	Aperiodic Signal	Fourier Transform
		$x[n]$ $y[n]$	$\left.\begin{matrix}X(e^{j\omega})\\ Y(e^{j\omega})\end{matrix}\right\}$ periodic with period 2π
5.3.2	Linearity	$ax[n] + by[n]$	$aX(e^{j\omega}) + bY(e^{j\omega})$
5.3.3	Time Shifting	$x[n - n_0]$	$e^{-j\omega n_0}X(e^{j\omega})$
5.3.3	Frequency Shifting	$e^{j\omega_0 n}x[n]$	$X(e^{j(\omega-\omega_0)})$
5.3.4	Conjugation	$x^*[n]$	$X^*(e^{-j\omega})$
5.3.6	Time Reversal	$x[-n]$	$X(e^{-j\omega})$
5.3.7	Time Expansion	$x_{(k)}[n] = \begin{cases} x[n/k], & \text{if } n = \text{multiple of } k \\ 0, & \text{if } n \neq \text{multiple of } k \end{cases}$	$X(e^{jk\omega})$
5.4	Convolution	$x[n] * y[n]$	$X(e^{j\omega})Y(e^{j\omega})$
5.5	Multiplication	$x[n]y[n]$	$\frac{1}{2\pi}\int_{2\pi} X(e^{j\theta})Y(e^{j(\omega-\theta)})d\theta$
5.3.5	Differencing in Time	$x[n] - x[n-1]$	$(1 - e^{-j\omega})X(e^{j\omega})$
5.3.5	Accumulation	$\sum_{k=-\infty}^{n} x[k]$	$\frac{1}{1-e^{-j\omega}}X(e^{j\omega}) + \pi X(e^{j0})\sum_{k=-\infty}^{+\infty}\delta(\omega - 2\pi k)$
5.3.8	Differentiation in Frequency	$nx[n]$	$j\frac{dX(e^{j\omega})}{d\omega}$
5.3.4	Conjugate Symmetry for Real Signals	$x[n]$ real	$\begin{cases} X(e^{j\omega}) = X^*(e^{-j\omega}) \\ \mathcal{R}e\{X(e^{j\omega})\} = \mathcal{R}e\{X(e^{-j\omega})\} \\ \mathcal{I}m\{X(e^{j\omega})\} = -\mathcal{I}m\{X(e^{-j\omega})\} \\ \lvert X(e^{j\omega})\rvert = \lvert X(e^{-j\omega})\rvert \\ \sphericalangle X(e^{j\omega}) = -\sphericalangle X(e^{-j\omega}) \end{cases}$
5.3.4	Symmetry for Real, Even Signals	$x[n]$ real an even	$X(e^{j\omega})$ real and even
5.3.4	Symmetry for Real, Odd Signals	$x[n]$ real and odd	$X(e^{j\omega})$ purely imaginary and odd
5.3.4	Even-odd Decomposition of Real Signals	$x_e[n] = \mathcal{E}v\{x[n]\}$ $[x[n]$ real] $x_o[n] = \mathcal{O}d\{x[n]\}$ $[x[n]$ real]	$\mathcal{R}e\{X(e^{j\omega})\}$ $j\mathcal{I}m\{X(e^{j\omega})\}$
5.3.9	Parseval's Relation for Aperiodic Signals $\sum_{n=-\infty}^{+\infty} \lvert x[n]\rvert^2 = \frac{1}{2\pi}\int_{2\pi} \lvert X(e^{j\omega})\rvert^2 d\omega$		

a duality relationship between the discrete-time Fourier transform and the continuous-time Fourier series. This relation is discussed in Section 5.7.2.

5.7.1 Duality in the Discrete-Time Fourier Series

Since the Fourier series coefficients a_k of a periodic signal $x[n]$ are themselves a periodic sequence, we can expand the sequence a_k in a Fourier series. The duality property for discrete-time Fourier series implies that the Fourier series coefficients for the periodic sequence a_k are the values of $(1/N)x[-n]$ (i.e., are proportional to the values of the original

TABLE 5.2: BASIC DISCRETE-TIME FOURIER TRANSFORM PAIRS

Signal	Fourier Transform	Fourier Series Coefficients (if periodic)
$\sum_{k=\langle N\rangle} a_k e^{jk(2\pi/N)n}$	$2\pi \sum_{k=-\infty}^{+\infty} a_k \delta\left(\omega - \frac{2\pi k}{N}\right)$	a_k
$e^{j\omega_0 n}$	$2\pi \sum_{l=-\infty}^{+\infty} \delta(\omega - \omega_0 - 2\pi l)$	(a) $\omega_0 = \frac{2\pi m}{N}$, $a_k = \begin{cases} 1, & k = m, m \pm N, m \pm 2N, \ldots \\ 0, & \text{otherwise} \end{cases}$ (b) $\frac{\omega_0}{2\pi}$ irrational $\Rightarrow$ The signal is aperiodic
$\cos \omega_0 n$	$\pi \sum_{l=-\infty}^{+\infty} \{\delta(\omega - \omega_0 - 2\pi l) + \delta(\omega + \omega_0 - 2\pi l)\}$	(a) $\omega_0 = \frac{2\pi m}{N}$, $a_k = \begin{cases} \frac{1}{2}, & k = \pm m, \pm m \pm N, \pm m \pm 2N, \ldots \\ 0, & \text{otherwise} \end{cases}$ (b) $\frac{\omega_0}{2\pi}$ irrational $\Rightarrow$ The signal is aperiodic
$\sin \omega_0 n$	$\frac{\pi}{j} \sum_{l=-\infty}^{+\infty} \{\delta(\omega - \omega_0 - 2\pi l) - \delta(\omega + \omega_0 - 2\pi l)\}$	(a) $\omega_0 = \frac{2\pi r}{N}$, $a_k = \begin{cases} \frac{1}{2j}, & k = r, r \pm N, r \pm 2N, \ldots \\ -\frac{1}{2j}, & k = -r, -r \pm N, -r \pm 2N, \ldots \\ 0, & \text{otherwise} \end{cases}$ (b) $\frac{\omega_0}{2\pi}$ irrational $\Rightarrow$ The signal is aperiodic
$x[n] = 1$	$2\pi \sum_{l=-\infty}^{+\infty} \delta(\omega - 2\pi l)$	$a_k = \begin{cases} 1, & k = 0, \pm N, \pm 2N, \ldots \\ 0, & \text{otherwise} \end{cases}$
Periodic square wave $x[n] = \begin{cases} 1, & \|n\| \le N_1 \\ 0, & N_1 < \|n\| \le N/2 \end{cases}$ and $x[n+N] = x[n]$	$2\pi \sum_{k=-\infty}^{+\infty} a_k \delta\left(\omega - \frac{2\pi k}{N}\right)$	$a_k = \frac{\sin[(2\pi k/N)(N_1 + \frac{1}{2})]}{N \sin[2\pi k/2N]}$, $k \ne 0, \pm N, \pm 2N, \ldots$ $a_k = \frac{2N_1 + 1}{N}$, $k = 0, \pm N, \pm 2N, \ldots$
$\sum_{k=-\infty}^{+\infty} \delta[n - kN]$	$\frac{2\pi}{N} \sum_{k=-\infty}^{+\infty} \delta\left(\omega - \frac{2\pi k}{N}\right)$	$a_k = \frac{1}{N}$ for all k
$a^n u[n]$, $\|a\| < 1$	$\frac{1}{1 - ae^{-j\omega}}$	—
$x[n] = \begin{cases} 1, & \|n\| \le N_1 \\ 0, & \|n\| > N_1 \end{cases}$	$\frac{\sin[\omega(N_1 + \frac{1}{2})]}{\sin(\omega/2)}$	—
$\frac{\sin Wn}{\pi n} = \frac{W}{\pi} \operatorname{sinc}\left(\frac{Wn}{\pi}\right)$ $0 < W < \pi$	$X(\omega) = \begin{cases} 1, & 0 \le \|\omega\| \le W \\ 0, & W < \|\omega\| \le \pi \end{cases}$ $X(\omega)$ periodic with period 2π	—
$\delta[n]$	1	—
$u[n]$	$\frac{1}{1 - e^{-j\omega}} + \sum_{k=-\infty}^{+\infty} \pi \delta(\omega - 2\pi k)$	—
$\delta[n - n_0]$	$e^{-j\omega n_0}$	—
$(n+1)a^n u[n]$, $\|a\| < 1$	$\frac{1}{(1 - ae^{-j\omega})^2}$	—
$\frac{(n+r-1)!}{n!(r-1)!} a^n u[n]$, $\|a\| < 1$	$\frac{1}{(1 - ae^{-j\omega})^r}$	—

TABLE 5.3: SUMMARY OF FOURIER SERIES AND TRANSFORM EXPRESSIONS

	Continuous time		Discrete time	
	Time domain	**Frequency domain**	**Time domain**	**Frequency domain**
Fourier Series	$x(t) = \sum_{k=-\infty}^{+\infty} a_k e^{jk\omega_0 t}$ continuous time periodic in time	$a_k = \frac{1}{T_0}\int_{T_0} x(t)e^{-jk\omega_0 t}$ discrete frequency aperiodic in frequency	$x[n] = \sum_{k=\langle N\rangle} a_k e^{jk(2\pi/N)n}$ discrete time periodic in time	$a_k = \frac{1}{N}\sum_{k=\langle N\rangle} x[n]e^{-jk(2\pi/N)n}$ discrete frequency periodic in frequency
Fourier Transform	$x(t) = \frac{1}{2\pi}\int_{-\infty}^{+\infty} X(j\omega)e^{j\omega t}d\omega$ continuous time aperiodic in time	$X(j\omega) = \int_{-\infty}^{+\infty} x(t)e^{-j\omega t}dt$ continuous frequency aperiodic in frequency	$x[n] = \frac{1}{2\pi}\int_{2\pi} X(e^{j\omega})e^{j\omega n}d\omega$ discrete time aperiodic in time	$X(e^{j\omega}) = \sum_{n=-\infty}^{+\infty} x[n]e^{-j\omega n}$ continuous frequency periodic in frequency

duality · duality · duality

- **TABLE 9.1**: PROPERTIES OF THE LAPLACE TRANSFORM

Section	Property	Signal	Laplace Transform	ROC
		$x(t)$ $x_1(t)$ $x_2(t)$	$X(s)$ $X_1(s)$ $X_2(s)$	R R_1 R_2
9.5.1	Linearity	$ax_1(t) + bx_2(t)$	$aX_1(s) + bX_2(s)$	At least $R_1 \cap R_2$
9.5.2	Time shifting	$x(t - t_0)$	$e^{-st_0}X(s)$	R
9.5.3	Shifting in the s-Domain	$e^{s_0 t}x(t)$	$X(s - s_0)$	Shifted version of R (i.e., s is in the ROC if $s - s_0$ is in R)
9.5.4	Time scaling	$x(at)$	$\frac{1}{\lvert a \rvert}X\left(\frac{s}{a}\right)$	Scaled ROC (i.e., s is in the ROC if s/a is in R)
9.5.5	Conjugation	$x^*(t)$	$X^*(s^*)$	R
9.5.6	Convolution	$x_1(t) * x_2(t)$	$X_1(s)X_2(s)$	At least $R_1 \cap R_2$
9.5.7	Differentiation in the Time Domain	$\frac{d}{dt}x(t)$	$sX(s)$	At least R
9.5.8	Differentiation in the s-Domain	$-tx(t)$	$\frac{d}{ds}X(s)$	R
9.5.9	Integration in the Time Domain	$\int_{-\infty}^{t} x(\tau)d(\tau)$	$\frac{1}{s}X(s)$	At least $R \cap \{\mathcal{R}e\{s\} > 0\}$

Initial- and Final-Value Theorems

9.5.10 If $x(t) = 0$ for $t < 0$ and $x(t)$ contains no impulses or higher-order singularities at $t = 0$, then

$$x(0^+) = \lim_{s \to \infty} sX(s)$$

If $x(t) = 0$ for $t < 0$ and $x(t)$ has a finite limit as $t \longrightarrow \infty$, then

$$\lim_{t \to \infty} x(t) = \lim_{s \to 0} sX(s)$$

- **TABLE 9.2**: LAPLACE TRANSFORMS OF ELEMENTARY FUNCTIONS

Transform pair	Signal	Transform	ROC
1	$\delta(t)$	1	All s
2	$u(t)$	$\frac{1}{s}$	$\mathcal{Re}\{s\} > 0$
3	$-u(-t)$	$\frac{1}{s}$	$\mathcal{Re}\{s\} < 0$
4	$\frac{t^{n-1}}{(n-1)!}u(t)$	$\frac{1}{s^n}$	$\mathcal{Re}\{s\} > 0$
5	$-\frac{t^{n-1}}{(n-1)!}u(-t)$	$\frac{1}{s^n}$	$\mathcal{Re}\{s\} < 0$
6	$e^{-\alpha t}u(t)$	$\frac{1}{s+\alpha}$	$\mathcal{Re}\{s\} > -\alpha$
7	$-e^{-\alpha t}u(-t)$	$\frac{1}{s+\alpha}$	$\mathcal{Re}\{s\} < -\alpha$
8	$\frac{t^{n-1}}{(n-1)!}e^{-\alpha t}u(t)$	$\frac{1}{(s+\alpha)^n}$	$\mathcal{Re}\{s\} > -\alpha$
9	$-\frac{t^{n-1}}{(n-1)!}e^{-\alpha t}u(-t)$	$\frac{1}{(s+\alpha)^n}$	$\mathcal{Re}\{s\} < -\alpha$
10	$\delta(t-T)$	e^{-sT}	All s
11	$[\cos\omega_0 t]u(t)$	$\frac{s}{s^2+\omega_0^2}$	$\mathcal{Re}\{s\} > 0$
12	$[\sin\omega_0 t]u(t)$	$\frac{\omega_0}{s^2+\omega_0^2}$	$\mathcal{Re}\{s\} > 0$
13	$[e^{-\alpha t}\cos\omega_0 t]u(t)$	$\frac{s+\alpha}{(s+\alpha)^2+\omega_0^2}$	$\mathcal{Re}\{s\} > -\alpha$
14	$[e^{-\alpha t}\sin\omega_0 t]u(t)$	$\frac{\omega_0}{(s+\alpha)^2+\omega_0^2}$	$\mathcal{Re}\{s\} > -\alpha$
15	$u_n(t) = \frac{d^n\delta(t)}{dt^n}$	s^n	All s
16	$u_{-n}(t) = \underbrace{u(t) * \cdots * u(t)}_{n \text{ times}}$	$\frac{1}{s^n}$	$\mathcal{Re}\{s\} > 0$

- **TABLE 9.3**: PROPERTIES OF THE UNILATERAL LAPLACE TRANSFORM

Property	**Signal**	**Unilateral Laplace Transform**
	$x(t)$ $x_1(t)$ $x_2(t)$	$\mathcal{X}(s)$ $\mathcal{X}_1(s)$ $\mathcal{X}_2(s)$
Linearity	$ax_1(t) + bx_2(t)$	$a\mathcal{X}_1(s) + b\mathcal{X}_2(s)$
Shifting in the s-domain	$e^{s_0 t}x(t)$	$\mathcal{X}(s - s_0)$
Time scaling	$x(at), \quad a > 0$	$\frac{1}{a}\mathcal{X}\left(\frac{s}{a}\right)$
Conjugation	$x*(t)$	$x*(s)$
Convolution (assuming that $x_1(t)$ and $x_2(t)$ are identically zero for $t < 0$)	$x_1(t) * x_2(t)$	$\mathcal{X}_1(s)\mathcal{X}_2(s)$
Differentiation in the time domain	$\frac{d}{dt}x(t)$	$s\mathcal{X}(s) - x(0^-)$
Differentiation in the s-domain	$-tx(t)$	$\frac{d}{ds}\mathcal{X}(s)$
Integration in the time domain	$\int_{0^-}^{t} x(\tau)\,d\tau$	$\frac{1}{s}\mathcal{X}(s)$

Initial- and Final-Value Theorems

If $x(t)$ contains no impulses or higher-order singularities at $t = 0$, then

$$x(0^+) = \lim_{s\to\infty} s\mathcal{X}(s)$$

$$\lim_{t\to\infty} x(t) = \lim_{s\to 0} s\mathcal{X}(s)$$

- **TABLE 10.1**: PROPERTIES OF THE z-TRANSFORM

Section	Property	Signal	z-Transform	ROC
		$x[n]$	$X(z)$	R
		$x_1[n]$	$X_1(z)$	R_1
		$x_2[n]$	$X_2(z)$	R_2
10.5.1	Linearity	$ax_1[n] + bx_2[n]$	$aX_1(z) + bX_2(z)$	At least the intersection of R_1 and R_2
10.5.2	Time shifting	$x[n - n_0]$	$z^{-n_0}X(z)$	R, except for the possible addition or deletion of the origin
10.5.3	Scaling in the z-domain	$e^{j\omega_0 n}x[n]$	$X(e^{-j\omega_0}z)$	R
		$z_0^n x[n]$	$X\left(\frac{z}{z_0}\right)$	z_0R
		$a^n x[n]$	$X(a^{-1}z)$	Scaled version of R (i.e., $\|a\|R$ = the set of points $\{\|a\|z\}$ for z in R)
10.5.4	Time reversal	$x[-n]$	$X(z^{-1})$	Inverted R (i.e., R^{-1} = the set of points z^{-1}, where z is in R)
10.5.5	Time expansion	$x_{(k)}[n] = \begin{cases} x[r], & n = rk \\ 0, & n \neq rk \end{cases}$ for some integer r	$X(z^k)$	$R^{1/k}$ (i.e., the set of points $z^{1/k}$, where z is in R)
10.5.6	Conjugation	$x^*[n]$	$X^*(z^*)$	R
10.5.7	Convolution	$x_1[n] * x_2[n]$	$X_1(z)X_2(z)$	At least the intersection of R_1 and R_2
10.5.7	First difference	$x[n] - x[n-1]$	$(1 - z^{-1})X(z)$	At least the intersection of R and $\|z\| > 0$
10.5.7	Accumulation	$\sum_{k=-\infty}^{n} x[k]$	$\frac{1}{1 - z^{-1}}X(z)$	At least the intersection of R and $\|z\| > 1$
10.5.8	Differentiation in the z-domain	$nx[n]$	$-z\frac{dX(z)}{dz}$	R
10.5.9		Initial Value Theorem If $x[n] = 0$ for $n < 0$, then $x[0] = \lim_{z \to \infty} X(z)$		

- **TABLE 10.2**: SOME COMMON z-TRANSFORM PAIRS

Signal	Transform	ROC
1. $\delta[n]$	1	All z
2. $u[n]$	$\dfrac{1}{1-z^{-1}}$	$\lvert z\rvert > 1$
3. $-u[-n-1]$	$\dfrac{1}{1-z^{-1}}$	$\lvert z\rvert < 1$
4. $\delta[n-m]$	z^{-m}	All z, except 0 (if $m > 0$) or ∞ (if $m < 0$)
5. $\alpha^n u[n]$	$\dfrac{1}{1-\alpha z^{-1}}$	$\lvert z\rvert > \lvert\alpha\rvert$
6. $-\alpha^n u[-n-1]$	$\dfrac{1}{1-\alpha z^{-1}}$	$\lvert z\rvert < \lvert\alpha\rvert$
7. $n\alpha^n u[n]$	$\dfrac{\alpha z^{-1}}{(1-\alpha z^{-1})^2}$	$\lvert z\rvert > \lvert\alpha\rvert$
8. $-n\alpha^n u[-n-1]$	$\dfrac{\alpha z^{-1}}{(1-\alpha z^{-1})^2}$	$\lvert z\rvert < \lvert\alpha\rvert$
9. $[\cos\omega_0 n]u[n]$	$\dfrac{1-[\cos\omega_0]z^{-1}}{1-[2\cos\omega_0]z^{-1}+z^{-2}}$	$\lvert z\rvert > 1$
10. $[\sin\omega_0 n]u[n]$	$\dfrac{[\sin\omega_0]z^{-1}}{1-[2\cos\omega_0]z^{-1}+z^{-2}}$	$\lvert z\rvert > 1$
11. $[r^n\cos\omega_0 n]u[n]$	$\dfrac{1-[r\cos\omega_0]z^{-1}}{1-[2r\cos\omega_0]z^{-1}+r^2z^{-2}}$	$\lvert z\rvert > r$
12. $[r^n\sin\omega_0 n]u[n]$	$\dfrac{[r\sin\omega_0]z^{-1}}{1-[2r\cos\omega_0]z^{-1}+r^2z^{-2}}$	$\lvert z\rvert > r$

- **TABLE 10.3**: PROPERTIES OF THE UNILATERAL z-TRANSFORM

Property	Signal	Unilateral z-Transform
—	$x[n]$	$\mathcal{X}(z)$
—	$x_1[n]$	$\mathcal{X}_1(z)$
—	$x_2[n]$	$\mathcal{X}_2(z)$
Linearity	$ax_1[n] + bx_2[n]$	$a\mathcal{X}_1(z) + b\mathcal{X}_2(z)$
Time delay	$x[n-1]$	$z^{-1}\mathcal{X}(z) + x[-1]$
Time advance	$x[n+1]$	$z\mathcal{X}(z) - zx[0]$
Scaling in the z-domain	$e^{j\omega_0 n}x[n]$ $z_0^n x[n]$ $a^n x[n]$	$\mathcal{X}(e^{-j\omega_0}z)$ $\mathcal{X}(z/z_0)$ $\mathcal{X}(a^{-1}z)$
Time expansion	$x_k[n] = \begin{cases} x[m], & n = mk \\ 0, & n \neq mk \quad \text{for any } m \end{cases}$	$\mathcal{X}(z^k)$
Conjugation	$x^*[n]$	$\mathcal{X}^*(z^*)$
Convolution (assuming that $x_1[n]$ and $x_2[n]$ are identically zero for $n < 0$)	$x_1[n] * x_2[n]$	$\mathcal{X}_1(z)\mathcal{X}_2(z)$
First difference	$x[n] - x[n-1]$	$(1 - z^{-1})\mathcal{X}(z) - x[-1]$
Accumulation	$\sum_{k=0}^{n} x[k]$	$\frac{1}{1 - z^{-1}}\mathcal{X}(z)$
Differentiation in the z-domain	$nx[n]$	$-z\frac{d\mathcal{X}(z)}{dz}$

Initial Value Theorem

$$x[0] = \lim_{z \to \infty} \mathcal{X}(z)$$

13